

# MS-SOHO INSTRUCTION MANUAL



**oliser**

Mesrutiyet caddesi. Hatay  
Sokak. 17/B

06640. Kızılay / Ankara

Turkey

**Tel :** +90 312 417 72 75

**Fax :** +90 312 425 72 81

**Web :** [www.oliser.com.tr](http://www.oliser.com.tr)

**Email :** [oliser@oliser.com.tr](mailto:oliser@oliser.com.tr)

## >>WARNING<<

### Suggestions when using Oliser's Inkjet Filling Machines

1. Oliser suggests using water when operating the machine for the first time
2. A pencil eraser can be used to clean the circuits on a cartridge

#### Maintenance :

Insert all Exhaust Lines into your specific catch receptable

**Note :** Empty your catch buckets once they become 1/3 full. This will optimize the air flow in your equipment and allow the System to perform correctly.

**Note :** Use separate catch buckets for waste and reusable liquids.

Flush your equipment with warm distilled water daily.

Simply use an empty cartridge to draw the distilled water through your equipment in place of ink.

This will keep any sediment from clogging the interior of the equipment.

#### Cleaning of VAC generator :

Take out the VAC generators connectors, put the VAC generator warm distilled water or cleaning solutions around five minutes, then apply compressed air through connectors one by one 3-5 seconds. Reconnect the connectors to the VAC generator and test the vacumm level before install into the machine.

**Maintenance procedure must be done regularly every week. OLISER is NOT responsible for the problems which is caused by un-maintenance...**

# BLACK FILLING CONTROL PANEL



You can select 4 different filling models by pressing left and right buttons. In order to see the contents of menu press enter.

Under HP menu;  
*15/45, 26-33, 27-A, 56, 29/14*  
cartridges appears. Press **READ** button to view prime/balance details. Then start filling by pressing **START**

Under Lexmark menu;  
*70/76, 13400, 3620, 0620, 0050, 0032, 0042, 0016*  
cartridges appears. Press **READ** button to view prime/balance details. Then start filling by pressing **START**

Under CANON menu;  
*02/X3, BC10, BC20, BC01*  
cartridges appears. Press **READ** button to view prime/balance details. Then start filling by pressing **START**

Under Xerox menu;  
*3855,0140,x310, c4, olivetti, 7879,7881*  
cartridges appears. Press **READ** button to view prime/balance details. Then



Under MANUAL menu;  
PIGMENT and DYE choices appear. Press **READ** button to view prime/balance details. Then



Press and hold ENTER button to adjust filling settings



Press -1 and +5 buttons to adjust filling amount.

## *In a class o its own*

Specifications:

- 1- Fills all black cartridges.
- 2- Advanced Menu system helps; effective cartridge filling.
- 3- Portable and easy to operate.
- 4- 110/220 V Switching power supply.

You can select the filling cartridge model by left and right arrows.

- HP ( *15/45, 26-33, 27-A, 56, 29/14* )
- Lexmark ( *70/76, 13400, 3620, 0620, 0050, 0032, 0042, 0016* )
- Canon ( *02/X3, BC10, BC20, BC01* )
- Xerox ( *3855,0140,x310, c4, olivetti, 7879,7881* )
- Manual ( By selecting manual, Dye and Pigment choices appear, and you can make adjustable ink filling )

By pressing and holding enter button setting menu appears and you can decrease or increase the filling amount. Under settings also Evac menu is available. Press enter to evacuate the cartridges with vacuum system.

### *Only entry-level machine for common-black inkjet cartridge refilling*

- It Fills, Evacuates and primes the abovementioned cartridges
- Filling and pressurizing operation is microcomputer controlled: - All cartridge models mentioned are stored in smart memory logic; with pre-determined pressure, ink ml quantity and sequence processing

## *Caters to sponge and bladder-based cartridges*

- Also boasts manual override feature for user-defined operation: For cartridges not featured here, yet desired by user for filling.
- No compressed air required
- Works on 110/220V (switching PSU)
- Very easy to use, You do not need to have special training: Simply insert the empty cartridge to the filling station; select cartridge type and push the Start / Stop button. You can cancel the filling operation at any time.
- Machine will fill the cartridge and perform auto-pressurizing / balancing.
- Thereafter immediately take the cartridge for print testing
- This machine is designed for use franchises, corner shops and the like.
- No optional extras: machine is shipped with all parts and auxiliary extras.
- 12 month warranty

**To Order Call: +90 312 417 72 75 or [oliser@oliser.com.tr](mailto:oliser@oliser.com.tr)**

# Tube replacement of motors

